



# PAN/TILT Surveillance USB Camera

www.mybluejay.com

*More Than Your Eyes Can See*

## BCP-401

The BCP-401 is designed for Personal and Home security surveillance applications. It is an ultimate security solution for your baby monitoring, health attendant as well as entrance surveillance.

It also makes online chats and instant messaging more fun. You can share live video and still images with your families over the internet instantly.

The BCP-401 features two tracking motors to pan and tilt the camera to moving object. It locks on to them, and records all activities of the movements.



### FEATURES

- Easy to install and set up with USB2.0 video class (UVC) interface
- Digital zoom up to 4X
- Motion Tracking Camera to pan and tilt with the moving object
- MSN Messenger, Yahoo Messenger, Windows Messenger, Smart Cam Plus, CrazyTalk and surveillance software supported
- Monitor and control four cameras from PC
- Store real-time video on motion detection
- Playback with adjustable speed
- Send alert with e-mail notification, window shaking, sound alarm
- Smart search recorded video streams by specific video region
- Built-in high sensitive microphone

### REGULATORY COMPLIANCE

- FCC/CE

### MECHANICAL

- Dimension : 70 x 70 x 100 mm (2.7 x 2.76 x 3.9 inch)
- Weight : 285g (19 oz)

### PACKAGE CONTENTS

- Web Camera
- USB2.0 with audio plug Y cable
- Setup CD
- Power adapter
- Mounting kit

### SPECIFICATIONS

- **Camera**
  - 1/4 inch Color CMOS Sensor
  - Effective Pixels : 300K pixels
  - Auto gain compensation/exposure/white balance
  - Fix focus
  - Focus range: 30cm~∞
  - Lens view angle: 64°
  - Motor tracking angle : Up/Down 60°, Left/Right 180°
- **Image**
  - Frame rate : 30fps@VGA/CIF
  - Maximum video/photo resolution : 1280x960
  - Digital Zoom : 4X
- **Hardware interface**
  - USB2.0, Type A
  - 3.5mm audio plug
  - Built-in microphone sensitivity: -40dB
  - Power LED
- **Operating environment**
  - Operating : 5°C ~ 40°C (41°F ~ 104°F)
  - Humidity : 5%-85% non-condensing
- **Power**
  - Charging through USB
  - Power consumption: 1.45W
- **Software**
  - OS : Microsoft Windows 2000/XP/Vista
  - Surveillance software : BlueJay Viewer
  - CrazyTalk Cam Suite, CrazyTalk Avatar Creator, USB driver

## Algolware Corporation

13F-5, No. 77, Sec.1, Sintai 5th Rd., Sijhih, Taipei, Taiwan (221), R.O.C.  
Tel : +886-2-2698-3689 Fax : +886-2-2698-3631

For more information go to : <http://www.mybluejay.com>