



Internet Camera

www.mybluejay.com

More Than Your Eyes Can See

BCN-600

The BlueJay Network Camera is specially designed for Home/SOHO/SME (small & medium enterprise) application. It allows you to watch your home, kids, workplace, and etc. anytime and anywhere in the world.

When connecting to the network over 10/100 Ethernet cable, you can use a Windows-based PC or Laptop computer to see, or to record the video streams, locally or through internet.

The BlueJay is the ultimate surveillance solution for your security needs.



FEATURES

- Motion detection & Alarm
- Alarm : E-mail, FTP, Relay output
- Sensor trigger and notify by E-mail or FTP
- Port assignable
- Dynamic IP Address : DDNS, DHCP, PPPoE-Service Name/User ID/User password
- Easy to install by simply connecting the camera to your local network or the Ethernet connection
- Monitor and control four cameras from PC anywhere
- Remote video surveillance from web browser(IE, Netscape, Firefox), PDA/Microsoft Smartphone, JAVA phone
- On-line viewing for multi-users simultaneously (maximum user : eight)
- Store real-time video on motion detection
- Playback with adjustable speed
- Send alert with e-mail notification, window shaking, sound alarm
- Smart search recorded video streams by specific video region
- Built-in high sensitive microphone
- Video display on a common household television

REGULATORY COMPLIANCE

- FCC/CE

MECHANICAL

- Dimension : 66 x 52 x 124 mm (2.6 x 2.1 x 4.9 Inch)
- Weight : 500 g (17.6 oz)

PACKAGE CONTENTS

- Network Camera
- Ethernet cable
- Setup CD
- Power adapter
- User manual & Quick installation guide
- Mounting Kit

SPECIFICATIONS

- **Camera**
 - 1/3" Color Sony Super CCD Sensor
 - Picture elements : 510x492(NTSC), 500x582(PAL)
 - Illumination : 0.1Lux / F1.2
 - Iris control : Video/DC Drive
 - Lens mount : C/CS mount (standard CS)
 - Back light comp. : On / Off
 - Auto Gain control/Exposure/White balance
- **Image**
 - Image compression : Motion JPEG
 - Frame rate : 20IPS(NTSC), 15IPS(PAL)
 - Video resolution : 640x480(NTSC), 704x576(PAL)
- **Hardware interface**
 - Video out: 1CH BNC, MJPEG compression
 - Audio out: 1CH RCA, AC-97 compression
 - Built-in high sensitivity microphone: mono
 - LAN connector: 10/100 BaseT Ethernet (RJ-45)
 - Serial connector: RS-232/RS-485
 - Alarm Input/Output: 1 / 1
 - Pan /Tilt /Zoom Control: PELCO D&P
- **Network**
 - TCP/IP, SMTP, FTP, NTP, DNS, DDNS and PPPoE
- **Operating environment**
 - Operating : 5°C ~ 45°C (41°F ~ 113°F)
 - Humidity : 30%-80% non-condensing
- **Power supply**
 - DC 12V / 0.5A power supply
- **Software**
 - OS : Microsoft Windows 2000/XP
 - Browser : IE 6.0 or above
 - Surveillance software : BlueJay Viewer
 - IP Cam Finder tool

Algolware Corporation

13F-5, No. 77, Sec.1, Sintai 5th Rd., Sijhih, Taipei, Taiwan (221), R.O.C.
Tel : +886-2-2698-3689 Fax : +886-2-2698-3631

For more information go to : <http://www.mybluejay.com>